

DIAM 4100

Single-phase Constant Current Regulator



www.augier.com



Multi Electric Mfg., Inc.

4223 W Lake Street Chicago, IL 60624 - Tel: 773.722.1900 Fax: 773.722.5694

sales@multielectric.com - www.multielectric.com



Compliance Standards

ICAO Aerodrome design manual, part 5
IEC (61822)
FAA (AC150/5345-10G – L829 - L828)
AENA (PPT002 ed4-2004)



Applications

DIAM4100 series CCRs are optimized static devices, controlled by two thyristors, designed to maintain a constant, pre-displayed and adjustable output current independently of load or power supply fluctuations. These devices are specifically designed for airfield lighting on runways, taxiways or aprons. They meet all international standards. DIAM4100 type CCR differs from the DIAM4000, (from which it takes all the electro technical and electric power part), by its electronics of innovating architecture built around an electronic board using a powerful DSP* processor, associated with an internal CAN* bus which links the different parts of the equipment.

A front USB* connector allows connection to a setting computer, this parameterization being possible *without live voltage*. Its control interface supports all series networks, with or without redundancy, as well as a universal multiwire interface.

Advantages

- **Use optimization :**

The powerful numerical processing capability of its microprocessor DSP* allows the best adaptation to all kind of loads (such as signs, for example) or special application. Emergency, warning messages as the current state of the CCR are displayed, on a simple and friendly HMI*.

- **Maintenance optimization :**

Its internal CAN* architecture has been designed to minimize the number and the variety of spare parts, and to allow the best flexibility of possible modification of options. Software tools are proposed in order to carry out fast parameter settings and/or diagnosis, without removing any parts. An automatic calibration avoids analogical adjustments, during maintenance operations.

- **Purchase and life-cycle costs optimization :**

DIAM4100 series constant current regulators represents the best trade-off on the market between high performances, maintenance services and the most reduced cost, thanks to an optimised design and a latest state-of-the-art digital electronic technology with DSP* and CAN* network, associated to fully experienced AUGIER's solutions for power electrotechnic and electrical parts and components.

DIAM 4100 : Technical Characteristics

GENERAL PRESENTATION

Each DIAM4100 is delivered into a metal frame with lifting rings. It includes 3 distinct parts: an "electronic" compartment, a "Low voltage" compartment and a "high voltage" compartment.

- The **Electronic part** includes an electronic board whose design uses the latest digital technologies; it is fixed at the front panel of the device. This front sheet supports the user interface delivering any useful information, and allowing all local or distant operations. Internal parts are accessible from the front or the top.
- The **Low voltage compartment** includes all components involved in supplying and controlling the device, as interface boards, fuses, terminals, thyristors. It is located at the rear in the upper part, and can be accessed removing the roof top or the back panel.
- The **High voltage compartment** is located at the lower part of the device, and includes components connected to the lighting loop, as the power transformer, lightning arrestors, load tapping and load terminals. It can be accessed opening the front panel of the CCR. A door contact switches the CCR off when opening the compartment, in order to avoid contact hazard with high voltage electrical parts.



MECHANICAL FEATURES

- Protection : IP 21. (other available on request).
- Dimensions (all powers and voltages) :
H 1380 mm, W 500 mm, D 700 mm.
with integrated circuit selector : H 1580mm, W 500mm, D 700mm.
- Axle track and wheelbase (if casters option): 355 x 610 mm.
- Use : temperature : -20°C (FAA style : -40°C to +55°C) to +55°C, humidity max. : 95%.
- Natural air cooling .
- Accessibility: In order to open front and back panels.
Distance min. between back and wall > 20 cm.

DIAM 4100 : Technical Characteristics

PROTECTIONS

- Lightning arrestors on outputs or input (option)
- Input circuit breaker instead of fuse (option)
- Overcurrent, Open circuit,
- Under/Over input voltage.

USER INTERFACE

Made up of a flat polyester keypad on the front plate, it includes a wide display of 16 x 140 pixels with screen saver , showing preferably on the upper line the installation state, warnings and parameters, and on the lower line the 4 keys definition, depending of the present menu.

An USB front socket allows the connection of a laptop computer, for a parameter setting possible without live voltage.



ELECTRICAL FEATURES

- Supply: Single-phase 208 to 480 Vac $\pm 10\%$ (IEC type) or $-5/+10\%$ (FAA type).
- Frequency : 50/60Hz $\pm 7.5\%$
- Output rated current : 6,6 A (20 A on request)
- Output rated power : from 1 kVA up to 30 kVA
- Power factor : FAA type : $> 90\%$ (2.5 to 10kW CCRs) or $> 95\%$ (15 to 30kW CCRs).
IEC type : $> 90\%$ at nominal voltage and rated resistive load.
- Efficiency : $> 90\%$ at rated parameters.
- Output current accuracy : Better than $\pm 1\%$ under the following conditions : Power supply voltage: $\pm 10\%$ (IEC) or $-5/+10\%$ (FAA) – Frequency: $\pm 7.5\%$, Load from 0 to 100%
- Remote control : Tension from 20V to 60V DC, or dry contacts, or serial single or double network.
- Back indication: Static dry contacts (IEC type), or relay contacts (FAA), or serial network
- Black current : preferred value 1.5 or 1.8 A

DIAM 4100 : Display and Menus


DISPLAY FUNCTIONALITY

The display shows 2 lines of text allowing to monitor many parameters, values and warnings. The lower line sets the definition of the keypad. The preferred information displayed can be changed in “STOP” mode, and can be chosen (long press on STOP) among the following possibilities :

- “Output current Io” – “brightness state Bx”
- “Output current Io” – “Output power Po”
- “Output current Io” – “Output voltage Uo”

DISPLAY EXAMPLES AND KEYS DEFINITION :


- “Stop” mode:



- “Local” mode : (B5 level). Press B+ or B- to increase / decrease the brightness :




- “Remote control” mode (B4 level):



ALARMS AND WARNINGS

All *alarms* (the CCR failed to supply the loop) and *warnings* (only indicative, without incidence on the loop) are clearly displayed.

- Example : “Open circuit” alarm : In order to restart, the fault shall be fixed first and then the alarm acknowledged, by pressing the “reset” key.



- Example : Earth Fault warning; in order to see what is the exact resistance value of the leakage (from 0 to 10 Mohms), go in the “monitoring” menu.



MONITORING

Parameters can be seen scrolling through the top-level menu items using the ← and → keys, after pressing OK :



DIAM 4100 : Display and Menus

CONFIGURATION MENU

The “*Configuration*” menu allows to set all basic parameters of the CCR to the processor (in case of mother board replacement, for example) :

- Rated input voltage, from 208 to 480 Vac
- Rated power, in kVA, from 1 to 30 kVA
- Brightness steps, from 1 to 8.
- Type : FAA or IEC

OPTION MENU

The “*Option*” menu allows the following definitions:

- Parameter access: *No*
A change from *No* to *Yes* allows the modification of all parameters of the DIAM4100, in order to avoid wrong operations.
- Scrolling items, all optional features of the CCR can be shown.


SETTING MENU

The “*Setting*” menu is used to assign all values of current and/or delays to brightness levels, current range (min. & max.), over current, open circuit fault detection, etc.

All these parameters are preferably set according to the current standard, but can be individually changed.

LOAD ADAPTATION


The output transformer is equipped with an epoxy plate including adjustment taps in order to adapt the rated output power of the CCR to the load. Moving 2 brass straps allows steps of 12.5%. Parameters of that position are then automatically memorized by the CCR, without other operation.



CUT-OUT AND EARTHING PLATE

In option, the CCR can be equipped with an earthing cut-out plate using 2 jumpers which allows to make all maintenance and measurement operations on the loop, without unscrewing any load or earth connections.

- “Normal” position: When the two 3 pins jumpers are in that position, the CCR supplies normally the load.
- “Safety” position: When the two jumpers are in that position, load and CCR are disconnected, short-circuited and grounded.



Note: other cut-out options are available (for more information, contact us).

* Notes :

- DSP : Digital Signal Processor
- CAN : Controller Area Network
- USB : Universal Serial Bus
- ECB : Equipement de Communication sur Boucle
- HMI : Human-Machine Interface

Constant Current Regulator - DIAM 4100

ORDERING INFORMATION

The DIAM4100 regulator is identified by a serial ordering code which indicates its type and particularity. If needed, add all useful precision and options.

Example : D41-IEC-1-5-50-15-400-B21-530 = DIAM4100 compliant to IEC, 6.6A, 5 brightness, 50Hz, 15kVA, 400Vac, with a multiwire interface (dry contacts) ,Jbus serial network, lightning arrestors on output terminals, Circuit breaker, EFD and LFD.

D 4 1 - I E C - 1 - 5 - 5 0 - 1 5 - 4 0 0 - B 2 1 - 5 3 0

Series D41 : DIAM 4100

Type IEC : IEC type
 828 : L-828 FAA Type (options as described in L828 advisory are included)
 829 : L-829 FAA Type (options as described in L829 advisory are included)
 AXX : AENA compliance (A29 = AENA PPT2-1995; A04 = AENA PPT2 / 04 / 04 / 2004)

Class 1 : Class 1 (ouptut current 6.6A)
 2 : Class 2 (output current 20A)

Style 3 : Style 1 (Class 1: 4.8A; 5.5A; 6.6A)
 5 : Style 2 : (Class 1: 2.8A; 3.4A; 4.1A; 5.2A; 6.6A, or Class 2: 8.5A; 10.3A; 12.4A; 15.8A; 20A)
 A : 5 brightness, AENA values
 X : Number of brightness, up to 8 (not counting B0 = « black » current) : values of currents must be specified separately

Frequency 50 : 50 Hz
 60 : 60 Hz

Output Power 01 : 1 kVA 05 : 5 kVA 15 : 15 kVA 30 : 30 kVA
 02 : 2.5 kVA 07 : 7.5 kVA 20 : 20 kVA
 04 : 4 kVA 10 : 10 kVA 25 : 25 kVA

Supply XXX : Input voltage : 208, 220, 230, 240, 277, 380, 400, 415 or 480 Vca -5% + 10% (FAA) or +-10% (IEC)

Control	0XX : No multiwire interface AXX : Internal source Remote Control BXX : External 20 to 60 Vdc Rem Control CXX : AENA Terminal Block DXX : Cylindrical sockets (SOURIAU) GXX : Internal 120 Vac remote control HXX : External 120 Vac remote control (Only one letter must be selected)	00X : No multiwire interface A1X or B1X : Negative common monitoring (IEC interface board) A2X or B2X : free common monitoring (FAA interface board, dry contacts) C2X D2X G2X H2X (Only one letter and number must be selected)	XX0 : No communication network XX1 : 1 x JBus RS485 port XX2 : 2 x JBus RS485 ports XX3 : 1 x lonwork port XX4 : 1 x Ethernet port XX5 : 1 x JBus and 1 x Ethernet port XX6 : 2 x ethernet ports (Only one letter must be selected)
----------------	---	---	--

Regular Options	0XX : No extra protection options 1XX : Lighting arrestors (outputs) 2XX : Lighting arrestors (inputs) 4XX : Circuit breaker (Final number : add all needed weights)	X0X : No extra monitoring options X1X : Earth fault detector (EFD) X2X : Lamp failure detector (LFD) X4X : Time meters (each brightness) (Final number : add needed weights)	XX0 : No extra options XX1 : Cut-out / earthing jumpers XX2 : Casters (unidirectional) XX4 : ECB included (Final number : add needed weights)
------------------------	--	--	---

If FAA type CCR, options as described in according advisory included)

Other Options : Complementary codes to add : BI (2 omni-directional caster with lock), CSx (circuit selesctor x-ways)
 Or specify : (FAA cut-out, IP other than IP 21).